INSTALLATION INSTRUCTIONS

Lighting fixture • universal instructions


Safety first: disconnect the power supply in the circuit before starting work and verify that no voltage is present.

Step-by-step installation

Prepare: a drill, pencil, plugs and screws suitable for the ceiling type, a screwdriver, and the wire terminals supplied with the fixture.


1 Disconnect power

Switch off the circuit breaker for the circuit where the fixture will be installed.




2 Mark the points

Hold the mounting bracket against the ceiling and mark the hole positions with a pencil.




3 Drill the holes

Drill holes at the marked positions, selecting a drill bit suitable for the substrate.




4 Insert the plugs

Insert the wall plugs into the drilled holes. Make sure they are seated securely.




5 Fasten the bracket

Align the bracket holes with the ceiling holes and fasten it with the screws.




6 Connect the wires

Connect the fixture wires to the electrical installation according to the terminal markings.



7 Attach the fixture

Fit the canopy and screw it to the bracket. Check that the fixture is stable.



OPERATING INFORMATION

Important information before commissioning and during use

Additional information

Shortening the cable

If required for the model, set the cable to the desired length and secure it with the clamp supplied in the kit.

Light source

After securing the fixture, screw in an E27 bulb (not included). Maximum power: 60 W or 12 W for an LED light source.

Connecting the wires

Carry out the connection only with the power disconnected. Connect the wires according to the markings on the fixture terminals and applicable regulations. If in doubt, contact a qualified electrician.

L	live
N	neutral
PE	protective earth - if present

Operation and safety

- Always disconnect the power before cleaning or replacing the bulb.
- Do not exceed the maximum light-source power: 60 W or 12 W LED.
- Clean the fixture with a soft, dry cloth; do not use abrasive products.
- Installation and connection to the existing electrical system should be carried out by a suitably qualified person.

WARNING

If you do not have the required knowledge and experience, have the installation carried out by a specialist. The fixture must be connected to an existing electrical installation.

Safety and handling symbols



Keep this instruction for future reference.

For questions, please contact the manufacturer:

Marcin Pędzijski MADECO
ul. Sucha 18 • 41-300 Dąbrowa Górnicza
biuro@madecohome.com • madecohome.com